

Route Ultra-HD 4Kx2K 60Hz 4:4:4 HDMI video and audio signals from many video sources to multiple displays.

- Configure and control the switch through front panel buttons, Ethernet, IR remote control, or RS232.
- Supports Ultra-HD 4Kx2K resolutions (4096x2160 and 3840x2160 @24/30/60Hz YUV 4:4:4) and HDTV resolutions to 1080p.
- Each input can be independently connected to any or all outputs.
- HDCP 2.2 compliant.
- HDMI features supported:
 - HDMI 2.0
 - Dolby TrueHD, DTS-HD Master Audio, Dolby Digital, DTS 7.1 and LPCM
 - YUV 4:4:4
 - HDR
 - 3D
 - Bandwidth up to 600 Mhz (18 Gbps)
 - Lip Sync
- Switch audio independently of video from connected HDMI sources (e.g. source 1 and source 2 video are active while only source 3 audio is active).
 - HDMI-embedded audio switching (four-channel stereo mixing)
 - SPDIF digital audio out ports for each source (8x8 model only).
- Configurable built-in EDID table
- Compact 1RU design
 - Mounting kit included



SM-8X8-4K18GB-LC (Front & Back)

The VEEMUX® Low-Cost 4K HDMI Matrix Switch routes digital 4Kx2K HDMI video and audio signals from up to eight HDMI video sources (computers, Blu-Ray players, satellite receivers, etc) to up to eight displays (monitors, 4K TV's, projectors, etc).

- **Resolutions to Ultra-HD 4Kx2K 60Hz 4:4:4**
- **HDMI 2.0, HDCP 2.2**
- **IR, RS232, Ethernet control**

Specifications

Inputs

- Female HDMI input connectors
- Four female 3.5mm ports for IR signal routing (4x4 model only).
 - IR frequency range: 38 to 56 kHz.
- Compatible with computers and UHD video sources (satellite receivers, Blu-Ray players, etc) with HDMI video.
- Supports HDCP 2.2/1.4

Outputs

- Female HDMI output connectors
- Four female 3.5mm ports for IR signal routing (4x4 model only).
 - IR frequency range: 38 to 56 kHz.
- Eight RCA jacks for SPDIF digital audio (8x8 model only).
- HDMI-embedded audio switching (four-channel stereo mixing).
- Supported resolutions
 - 4Kx2K (4096x2160 and 3840x2160) @24Hz/30Hz/60Hz YUV 4:4:4
 - 480p @60Hz, 576p@50Hz, 720p@60Hz, 1080p @24/50/60Hz
- Supports HDCP 2.2/1.4
- Video bandwidth: 600MHz (18 Gbps)

Power

- Input: 100 to 240 VAC at 50 or 60 Hz via AC adapter (AC adapter included.)
- Output: 12VDC, 3.0A
- Power consumption:
 - SM-4X4-4K18GB-LC: 12W
 - SM-8X8-4K18GB-LC: 19W

Dimensions

- WxDxH (in):
 - SM-4X4-4K18GB-LC: 17.24x8.66x1.75 (438x220x44 mm).
 - SM-8X8-4K18GB-LC: 17.32x8.66x1.75 (440x220x44 mm).

Cables

- Use HD-xx-MM HDMI cables to connect an HDMI source or display.
 - SM-4X4-4K18GB-LC: Supports cable lengths to 25 feet for 4Kx2K resolutions at 60Hz and lengths to 50 feet for 4Kx2K resolutions at 30Hz.
 - SM-8X8-4K18GB-LC: Supports cable lengths to 50 feet for 4Kx2K resolutions at 60Hz
- Cables not included.

Regulatory Approvals

- CE, FCC, RoHS

Warranty

- Two years

Package Includes

- One 4K HDMI Video Matrix Switch
- One power adapter
- One IR remote
- One IR extension cable
- Four IR transmission cables (4x4 model only).
- Four IR receiver cables (4x4 model only).
- Mounting kit
- CD with software and user manual

Low-Cost 4K HDMI Video Matrix Switch: 4x4, 8x8

VEEMUX®

Route Ultra-HD 4Kx2K 60Hz 4:4:4 HDMI video and audio signals from many video sources to multiple displays.

Specifications (continued)

Environmental

- Operating temperature:
 - SM-4X4-4K18GB-LC: 32 to 104°F (0 to 40°C).
 - SM-8X8-4K18GB-LC: -4 to 140°F (-20 to 60°C).
- Storage temperature:
 - SM-4X4-4K18GB-LC: -4 to 140°F (-20 to 60°C).
 - SM-8X8-4K18GB-LC: -40 to 158°F (-40 to 70°C).

Compatible NTI Products

- Combine NTI's extenders, switches, splitters and cables for complex applications
 - 4K HDMI Extender via One CATx (ST-C64K-300)
 - Each output on the switch must be set to 3840x2160 @ 30Hz.

Control Methods

Front Panel Interface

- Standard control method
- Configuration and control can be done using the front panel buttons.
- Keypad allows selection of the input source to be routed to the desired outputs.

Ethernet Control

- Standard control method.
- Configuration can be done over the Internet via Web server.
- Female RJ45 connector.
- 10/100 BaseT Ethernet interface.

RS232 Control

- Standard control method
- Configuration and control can be done through the serial port.
 - Female DB9 connector.
- Control the switch using the Control Program with Graphical User Interface (GUI control) via RS232. (Control software included.)

Infrared Remote Control

- Standard control method
- IR control of matrix switch:
 - The matrix switch can be controlled locally with the included IR remote using the built-in IR receiver on the switch.
 - Extend IR control up to 3.9 feet (1.2 meters) with IR extension cable (included).
 - One female 3.5mm port for IR extension.
- Route IR signal for source/displays. (4x4 model only)
 - Full Infrared Remote (IR) control of HDMI source/display using existing source/display remote control.

Low-Cost 4K HDMI Video Matrix Switch: 4x4, 8x8

NTI Part #	HDMI Inputs	HDMI Outputs
SM-4X4-4K18GB-LC	4	4
SM-8X8-4K18GB-LC	8	8

Configuration and Cable Illustration

