



**NETWORK
TECHNOLOGIES
INCORPORATED**

1275 Danner Dr. Tel:330-562-7070
Aurora, OH 44202 Fax:330-562-1999
www.networktechinc.com

VGA-DVI

VGA-DVI Converter User's Guide



Check your package

Check the package and make sure you have everything:

Contents

- (1) VGA to DVI Converter
- (2) +5V DC Power supply x 1pc
- (3) User's Guide

Installation

Installation Steps:

1. Connect the included +5V DC power supply to VGA-DVI and check power LED indicator become active.
2. Select front VGA input switch between RGB and YPbPr.
3. Select front VGA output switch between Bypass and RGB.
4. Connect the source device to VGA input port.



Installation

5. Connect the display device to VGA-DVI DVI output port.
6. Connect the monitoring display to VGA-DVI VGA output port.
7. Resolution LED indicator will glow bright green.



Key name	Description
Default	Return to factory setting 1. Return to the factory setting for screen location: Press the default key once. All LED indicators will blink twice. 2. Return to the factory setting for EDID preset: Press the default key for 2 seconds. LED indicators blink sequentially from left to right.
Up/Down/Right/Left	1. Adjust screen location (for DVI output only) 2. Change EDID setting

How to change EDID setting

VGA-DVI is designed to be able to change internal EDID program by user. VGA-DVI supports WUXGA/1080p/UXGA/SXGA 4 kind of EDID programs.

<How to change EDID setting>

1. According to the table below, press the two direction keys simultaneously for three seconds.
2. The resolution LED you want to change will blink twice, and return to the resolution LED which currently set.
3. Reboot the computer.

EDID	Key
WUXGA(1920x1200)	Up(▲) / Left(◀)
1080p(1920x1080)	Up(▲) / Right(▶)
UXGA(1600x1200)	Up(▲) / Down(▼)
SXGA(1280x1024)	Up(▲) / Default