

BNC/RCA Composite Video + S-Video to VGA Converter

VIDEO CONVERTERS

Converts BNC and S-Video signals into VGA video.

- Supports resolutions to 1920x1200.
- Auto-detects NTSC/PAL inputs.
- Compatible with VGA/SVGA monitors, including LCD flat panel monitors.
- Adjust video brightness, contrast, saturation, and hue.
 - Auto-saves settings and working status when powered down.
- Includes a male BNC to female RCA adapter for connecting RCA composite video devices.



BNCSV-VGA-CNVTR (Front & Back)

The BNC/RCA Composite Video + S-Video to VGA Converter changes Composite video and S-Video signals from surveillance DVRs, security cameras, quad video processors, etc. into a VGA output for computer monitor displays.

Specifications

Video Input

- One female BNC connector.
- One female S-Video connector.
- One female VGA connector.
- Includes a male BNC to female RCA adapter for connecting RCA composite video devices.
- Supports NTSC/PAL.

Video Output

- One female VGA connector.
- Output resolutions:
 - 4:3 screen: 800x600@60/75Hz, 1024x768@60Hz, 1280x1024@60Hz, 1600x1200@60Hz.
 - 16:9/16:10 screen: 1280x720@60Hz, 1366x768@60Hz, 1440x900@60Hz, 1600x900@60Hz, 1680x1050@60Hz, 1920x1080@60Hz, 1920x1200@60Hz.

Power

- 100 to 240 VAC at 50 or 60 Hz via AC adapter.

Dimensions

- WxDxH (in): 4.13x2.33x0.90 (105x59x23 mm).

Warranty

- Two years.

Cables

- 5 ft (1.5 m) S-Video cable included.
- Male BNC to female RCA adapter included.